

Santak CASTLE RACK C3KR On-Line 3000VA/2400W Rack UPS

Santak CASTLE C3KR On-Line 3000VA/2400W Rack UPS

Power rating	3 kVA
Input	Input Voltage Range: (110-300)VAC Frequency Range: 40-70 Hz Input Power Factor: $\geq 0,98$
Output	Nominal Output Voltage: $220*(1\pm 2\%)$ VAC Frequency Range: sync with line of ± 4 Hz(Line mode), 50 ± 0.05 Hz (Battery mode) Output Power Factor: 0.9@30°C and 0.8@40°C Overload capacity: 105%-150% $\square$ 47s-25s $\square$ 150%-200% $\square$ 25s-300ms $\square$ >200% $\square$ 200ms (0.8PF) Outlet: IEC C13*3 pcs + C19*1 pc
Battery and charger	Tegangan Pengenal Baterai: 72V Type: Maintenance-free Sealed Lead-acid UPS Batteries Number of Internal Battery: 6PCS Recharge Current: 1A
Waktu Transfer	Battery Mode<-->InverterMode 0ms Inverter Mode<-->BypassMode 4ms (typical)
Backup time (80% load, 0.8PF)	>4,5 mnt
Indicator	LED: Load, battery capacity, UPS working mode

Alarm	Battery full: 1buzzing/4s; Battery empty: 1buzzing/1s Alarm UPS: Buzzing continue
Auto restart	Auto restart while mains recover
Interface	USB: Monitoring Optional Parts: NMC Card, Modbus Card, Relay Card
Environment	Temperature: 0°C-40°C Humidity: 0-95%, non-condensing
Net Weight	21,6
Dimension (W*D*H)	438 x 570 x 87